Product data sheet

Power connectors




Product description M23 square male panel mount connector, Contacts: 12, shielding is not possible, solder, IP67, back mounting

Area **M23 series 623** Order number **99 4607 81 12**

Illustration





1	-3,60	4,30
2	-5,55	1,00
3	-4,90	-2,80
4	-1,90	-5,30
5	1,90	-5,30
6	4,90	-2,80
7	5,55	1,00
8	3,60	4,30
9	0,00	4,50
10	-1,90	1,00
11	0,00	-2,20
12	1,90	1,00

Technical data

General values

Connector design

Connector locking system Termination Arrangement of contacts Wire gauge (mm) Wire gauge (AWG) Upper limit temperature Lower limit temperature Customs tariff number Packaging Unit square male panel mount

connector screw solder left-handed max. 1.00 mm² max. 17 125 °C – 20 °C 85369010

Electrical values

Rated current (40 °C) 8 A
Rated voltage 150 V
Rated impulse voltage 1500 V
Pollution degree 3
Overvoltage category II
Insulating material group IIII
Insulation resistance ≥ 10¹⁰ Ω

EMC compliance shielding is not possible Degree of protection IP67

Mechanical operation > 50 Mating cycles

Material

Contact material Contact plating Contact body material Housing material REACH SVHC CuZn (brass) Au (gold) PBT/PA66 Zinc die-cast nic

Zinc die-cast nickel-plated CAS 7439-92-1 (Lead)

Product data sheet

Power connectors



Product description M23 square male panel mount connector, Contacts: 12, shielding is not possible, solder, IP67, back mounting

Area **M23 series 623** Order number **99 4607 81 12**

Security notices

The connector must not be connected or separated under load. Non-observance and incorrect use can result in personal injury.

The connectors are designed for use in plant, control system and electrical equipment. The end user is responsible for checking whether the connectors are suitable for use in other applications.

Connectors with degree of protection IP 67 and IP 68 are not suitable for use under water. When used outdoors, the connectors must be separately protected against corrosion. For further information about IP degrees of protection refer to 'Technical support' in the Download Centre.