
Product data sheet Miniature connectors



Product description

Snap-In IP67 female panel mount connector, Contacts: 3, shielding is not possible, dip-solder, IP67, VDE

Area Order number Snap-In IP67 series 720 99 9108 090 03



You can find the component part drawing and assembly instructions on the next page.

Technical data

General values

Connector design Connector locking system Termination Wire gauge (mm) Wire gauge (AWG) Upper limit temperature Lower limit temperature Customs tariff number Packaging Unit

Cable data

Approval 1

female panel mount connector snap dip-solder max. 0.75 mm² max. 18 85 °C - 25 °C 85369010 100

VDE

Electrical values

Rated current (40 °C) Rated voltage Rated impulse voltage Pollution degree Overvoltage category Insulating material group Insulation resistance EMC compliance Degree of protection Mechanical operation

Material

Contact material Contact plating Contact body material Housing material REACH SVHC 7 A 250 V 2500 V 2 II II $\geq 10^{10} \Omega$ shielding is not possible IP67 > 500 Mating cycles

CuSn (bronze) Au (gold) PA (UL94 V-0) PA CAS 7439-92-1 (Lead)




Product data sheet Miniature connectors




Product description

Snap-In IP67 female panel mount connector, Contacts: 3, shielding is not possible, dip-solder, IP67, VDE

Area Order number Snap-In IP67 series 720 99 9108 090 03







Product data sheet Miniature connectors



Product description

Snap-In IP67 female panel mount connector, Contacts: 3, shielding is not possible, dip-solder, IP67, VDE

Area Order number Snap-In IP67 series 720 99 9108 090 03

Security notices

The connector must not be connected or separated under load. Non-observance and incorrect use can result in personal injury.

The connectors are designed for use in plant, control system and electrical equipment. The end user is responsible for checking whether the connectors are suitable for use in other applications.

Connectors with degree of protection IP 67 and IP 68 are not suitable for use under water. When used outdoors, the connectors must be separately protected against corrosion. For further information about IP degrees of protection refer to 'Technical support' in the Download Centre.

